

### J-Link 2mm Adapter

The J-Link 2mm Adapter adapts from the standard 20-pin J-Link connector to a 20-pin 2mm-pitch connector. The J-Link 2mm Adapter is a 1:1 adapter, since the pinout of the 2mm pitch connector is identical to the standard 20-pin J-Link connector.



VTref	1 ● ● 2	---
nTRST	3 ● ● 4	GND
TDI	5 ● ● 6	GND
TMS	7 ● ● 8	GND
TCK	9 ● ● 10	GND
RTCK	11 ● ● 12	GND
TDO	13 ● ● 14	GND
RESET	15 ● ● 16	GND
DBGREQ	17 ● ● 18	GND
5V-Supply	19 ● ● 20	GND

Pins 14, 16, 18, 20:

On some models like the high-end model J-Link PRO, these pins may not be connected to GND but are reserved for future use/extension. In case of doubt, leave open on target hardware.